

Lamps with metal bases P21/4W

Original spare part



The cost-effective original spare parts

ORIGINAL signal lamps with metal bases feature - like all ORIGINAL products from OSRAM - a reliable OEM quality. Due to the wide product range, the lamps can be used as original spare lamps for different applications.

Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference	7225
------------------------	------

Electrical Data

Power input	25 / 5 W
Nominal voltage	12.0 V
Test voltage	13.5 / 13.5 V
Power input tolerance	±6 / ±10 %

Photometric Data

Nominal luminous flux	440/15 lm
Luminous flux tolerance	±15 / ±20 %

Physical Attributes & Dimensions

Diameter	25.0 mm
Product weight	10.00 g
Length	49.5 mm
Lamp base	BAZ15d

Lifetime Data

Lifespan B3	180 / 1250 hr ¹⁾
Lifespan Tc	290 / 4000 hr ¹⁾

¹⁾ Filament 1 / Filament 2

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	P21/4W
Approval marks – approval	E1 approval

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	09-07-2024

Product datasheet

Primary article identifier	4008321593009 4062172121378 4052899402119 4008321671875 4050300925547 4062172121033 4008321163974 4050300891514 4062172396226 4062172091749 4062172396202
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321091093	ORIGINAL - METAL BASE P21/4W		- x - x -	2.57 dm ³	
4008321140531	ORIGINAL - METAL BASE P21/4W		- x - x -	2.31 dm ³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM